



Digital Mixer Amplifier with MP3/Tuner/Bluetooth (Phoenix Mic Input)

T-B120DTB



Product Introduction

It is the mixer amplifier with mp3/TUNER/Bluetooth for small and medium sized background music occasion such as small supermarkets, shopping malls, and cafes.

Features

- * Standard rack mounted design (1U), exquisite SMT process design.
- * With MP3 function module, adopt LCD display, support playback of various file formats in U disk such as MP3, WMA, APE, FLAC, WAV, and AAC; with TF card, support mobile phone Bluetooth function, and can display song names.
- * Support mp3/TUNER/Bluetooth remote control function.
- * 1 channel EMC input, 2 channels AUX input, 4 channels MIC input.
- * Channel priority: EMC > MIC1 > MIC2, MIC3, AUX1, AUX2.
- * Each channel has independent volume control function; master input has volume control and treble/bass control.
- * MIC1-4 supports balanced input, built-in 48V phantom power.
- * The machine is equipped with level indication, overload and protection indicator.
- * The device has good self-protection such as short circuit, overload and overheating.
- * Two output modes: constant voltage output 100V, constant resistance output 4-16Ω.
- * Energy-efficient switching power supply combines with energy-saving and ultra-stable design of Class D amplifiers.
- * Support backup power supply 24V switching without delay (optional).

Specifications

| | |
|--|--|
| Model | T-B120DTB |
| Output | 4-16Ω, 100V |
| RMS Power | 120W |
| Input Sensitivity & Impedance | MIC1, 2, 3, 4 input: 5mV/600Ω balanced European connection terminal AUX1, 2 input: 350mV/10KΩ unbalanced RCA connection terminal EMC input: 775mV/10KΩ unbalanced European connection terminal MIX OUT: 1000mV/470Ω, unbalanced RCA connector |
| Output Sensitivity & Source Impedance | |
| Tone | Bass: ±10dB at 100Hz; Treble: ±10dB at 10KHz |
| Frequency Response | 80Hz~16KHz(+1dB,-3dB) |
| SNR | MIC1, 2, 3: 66dB; AUX1, 2: 80dB |
| THD | Less than 0.5% (at 1KHz, 1/3 rated power) |
| Mute Control | MIC 1 priority over MIC2-4, AUX1-2 audio input; EMC has highest priority |
| Channel Crosstalk Attenuation | ≥50dB |
| Heat Dissipation | Flank in and rear panel out to force fan cooling, fan starts when amplifier turned on, infinitely variable speed |
| Protection | Over-heat, overload, short circuit |
| Power Supply | AC ~220-240V /50Hz |
| Power consumption | 180W |
| Dimension | 484×300×44mm |
| Weight | 3.7Kg |

Rear Panel

